## **CAHSS100P** (-40°C)





- Insulated stainless steel cabinet
- Frost resistant down to (-40 °C)
- Additional frontal heating element (-20 °C to -40 °C)
- Fan for ventilation
- 2 x LED lights (meaning defibrillator is visible in the dark)
- Designed to be easy to open, even under conditions of heavy snow and frost.
- Future-proof! (Software can be upgraded)

## FUNCTIONAL DESCRIPTION:

If the door of the cabinet is opened... The SIREN immediately sounds.

(if the door of the cabinet is closed once again within 3 minutes the siren will stop automatically)

Once the door is closed... The cabinet is once again ready for operation.

## TECHNICAL DESCRIPTION:

The door is fitted with thermopane glass and marked with international AED labels/symbols. Door.

Light: 2 x LED lights in the cabinet, such that the defibrillator is visible in the dark.

Siren: Siren in the cabinet. (100 dBA / 1m)

Ventilation fan, starts automatically when temperature exceeds +40 °C. Fan:

Frost-prof cabinet: Thermostatically-controlled heating element. Frost resistant down to -40 °C

Voltage: Must be connected to a 230V (116Wh) electrical supply.

Outdoor cable (3 x 1.5 mm²) Cat II, IE IEC 61010-1 Overvoltage category:

Protection rating: IP43. Ambient temperature: -40 / +40°C Relative humidity: 0 - 95 %

Environmental pollution degree:

Altitude: Max. 2000 masl. (meters above sea level)

IEC61010 - with deviations in insulation fire class and service switch. Design norm:

Insulation - fire class: E / F (EN13501)

External dimensions:  $W \times H \times D = 44 \times 46 \times 27 \text{ cm}$  (incl. door handles)

Internal dimensions:  $W \times H \times D = 33 \times 38 \times 20 \text{ cm}$ 

Weight: Gross weight incl. packaging 18.5 kg.

## MAINTENANCE / CLEANING:

We recommend cleaning the outer surface of the cabinet at least 1-2 times per year.

Wipe using detergent and a damp cloth or brush and rinse with clean water. Finally wipe down the cabinet with a dry cloth.

If the surface of the cabinet becomes tarnished, this will be due to deposits which can easily be cleaned off. For difficult deposits, use a scouring pad. Never use wire wool.